

**BS3607****3 1/2 digits LCR multimeter**

## Features:

- 3 1/2 Digits large LCD display
- DC Voltage 200mV to 600V
- AC Voltage 2V to 600V
- DC Current 200mA to 20A
- AC Current 200mA to 20A
- Resistance 200Ω to 20MΩ
- Capacitance 2nF to 200μF
- Inductance 2mH to 20H
- Diode test
- Continuity test
- Transistor test
- Low Battery Warning
- Auto Power Off
- Data Hold
- Conform to IEC1010/EN61010-1, CE-EMC & LVD CATII 600V

**General Specifications**

Display	: 3 1/2 digits LCD with max. reading of 1999.
Polarity	: Automatic, (-) negative polarity indication.
Zero adjustment	: Automatic.
Over range indication	: Only the MSD "1" is displayed.
Power	: Single, standard 9 volt battery NEDA 1604, JIS 006P, IEC6F22.
Dimension	: 94 (W) x 205 (H) x 62 (D) mm.
Weight	: Approx. 620 g (including battery).

### Electrical Specification

Accuracies are  $\pm$ (% of reading + number of least significant digits) at  $23^{\circ}\text{C}\pm 5^{\circ}\text{C}$ , less than 75%RH

#### DC Voltage Measurement

Range	Resolution	Accuracy	Input Impedance	Overload Protection
200mV	0.1mV	$\pm(0.8\% \text{ Read.} + 1\text{dgt})$	10M $\Omega$	250V DC/AC rms
2V	0.001V			600V DC/AC rms
20V	0.01V			
200V	0.1V			
600V	1V			

#### AC Voltage Measurement

Range	Resolution	Accuracy	Input Impedance	Overload Protection
2V	0.001V	$\pm(0.8\% \text{ Read.} + 3\text{dgt})$	10M $\Omega$	600V DC/AC rms
20V	0.01V			
200V	0.1V			
600V	1V	$\pm(1.2\% \text{ Read.} + 3\text{dgt})$		

**Frequency range: 40-400Hz**

#### DC Current Measurement

Range	Resolution	Accuracy	Voltage drop	Overload Protection
200mA	0.1mA	$\pm(1.0\% \text{ Read.} + 5\text{dgt})$	200mV	Fast 2A/250V Fuse
20A	0.01A	$\pm(2.0\% \text{ Read.} + 10\text{dgt})$		Unfused 15sec.

**AC Current Measurement**

Range	Resolution	Accuracy	Voltage drop	Overload Protection
200mA	0.1mA	$\pm(1.2\% \text{ Read.} + 10\text{dgt})$	200mV	Fast 2A/250V Fuse
20A	0.01A	$\pm(2.5\% \text{ Read.} + 10\text{dgt})$		Unfused 15sec.

**Frequency range: 40-400Hz****Resistance Measurement**

Range	Resolution	Accuracy	Open circuit voltage	Overload Protection
200 $\Omega$	0.1 $\Omega$	$\pm(1.0\% \text{ Read.} + 4\text{dgt})$	<0.7V	250V DC/AC rms <30 sec
2k $\Omega$	0.001k $\Omega$	$\pm(0.8\% \text{ Read.} + 4\text{dgt})$		
20k $\Omega$	0.01k $\Omega$			
200k $\Omega$	0.1k $\Omega$			
2M $\Omega$	0.001M $\Omega$		<3.0V	
20M $\Omega$	0.01M $\Omega$	$\pm(2.0\% \text{ Read.} + 2\text{dgt})$		

**Capacitance Measurement**

Range	Resolution	Accuracy	Overload Protection
2nF	0.001nF	$\pm(2.5\% \text{ Read.} + 5\text{dgt})$	250V DC/AC rms <30 sec.
20nF	0.01nF		
200nF	0.1nF		
2 $\mu$ F	0.001 $\mu$ F		
20 $\mu$ F	0.01 $\mu$ F		
200 $\mu$ F	0.1 $\mu$ F	$\pm(5.0\% \text{ Read.} + 4\text{dgt})$	

**Inductance Measurement**

Range	Resolution	Accuracy	Overload Protection
2mH	0.001mH	±(2.0 Read. + 10t)	250V DC/AC rms <30 sec.
20mH	0.01mH		
200mH	0.1mH		
2H	0.001H		
20H	0.01H		

**Diode Test**

Range	Accuracy	Open circuit voltage	Overload Protection
▶+	Approx. 1mA	2.8V	250V DC/AC rms <30 sec

**Continuity Test**

Range	Buzzer sounds when resistance value < 60Ω	Open circuit voltage	Overload Protection
•))		2.8V	250V DC/AC rms <30 sec

**Transistor Test**

Range	hFE value	Base current	Open circuit voltage	Overload Protection
hFE	0-1000	Approx. 10μA	Approx. 2.8V	250V DC/AC rms <30 sec.

**CALTEK INDUSTRIAL (HONG KONG) LIMITED**[www.bstcaltek.com](http://www.bstcaltek.com)Hong Kong Office

Address: Unit 11 10/F, Kwai Cheong Center, 50 Kwai Cheong Road, Kwai Chung, N.T., Hong Kong

Email: [caltek@caltek.com.hk](mailto:caltek@caltek.com.hk)

Tel: (852) 2401-1222

Fax: (852) 2420-3472

Singapore Office

Level 15, Suite 27, Prudential Tower, 30 Cecil Street, Singapore 049712

Email: [caltek\\_sg@caltek.com.hk](mailto:caltek_sg@caltek.com.hk)

Tel: (65) 6232-2903

Fax: (65) 6232-2888